

| DRIVER | Helvar | | | | | | | | | | | | |
|--------------|-------------|----------------|-------------|---|-------------|----------------------------|-------------|---------------|--------|--------|--------|---------|-------|
| | LL1x12-E-CC | LL1x10-42-E-CC | LL1x20-E-CC | LC1x30-E-CC LC1x30-E-DA LC1x30-E-AN | OL1x60-E-CC | LL1x70-E-CC LL1x70-E-DA | LL1x80-E-CC | OL1x100-E-CC1 | | | | | |
| MODULO LED | 350mA | | 700mA | | 350mA | | 700mA | | 350mA | | 700mA | | |
| | ML9R1AL | 1 a 3 | 4 a 12 | 2 a 5 | — | 2 a 6 | — | 7 a 9 | — | 6 a 20 | — | 13 a 23 | — |
| ML12R2AH4500 | — | — | — | — | — | 1 | — | 1 a 2 | — | 2 | — | 2 a 3 | 2 a 3 |
| ML14R3AH4500 | — | — | — | — | — | 1 | — | 1 a 2 | — | 2 | — | 2 | 2 |
| ML15R1AL | 1 a 2 | 2 a 7 | 1 a 3 | — | 4 a 5 | — | 4 a 5 | — | 4 a 12 | — | 8 a 14 | — | — |
| ML15R4FL | 1 a 2 | 2 a 7 | 1 a 3 | — | 4 a 5 | — | 4 a 5 | — | 4 a 12 | — | 8 a 14 | — | — |
| ML18R1AL | 1 | 2 a 6 | 1 a 2 | — | 4 | — | 4 | — | 3 a 10 | — | 7 a 11 | — | — |
| ML18R5FL | 1 | 2 a 6 | 1 a 2 | — | 4 | — | 4 | — | 3 a 10 | — | 7 a 11 | — | — |
| ML24R5FL | 1 | 2 a 4 | 1 a 2 | — | 3 | — | 3 | — | 2 a 7 | — | 5 a 8 | — | — |
| ML30R6FL | 1 | 1 a 3 | 1 | — | 2 | — | 2 | — | 2 a 6 | — | 4 a 7 | — | — |
| ML33R7FL | 1 | 1 a 3 | 1 | — | 2 | — | 2 | — | 2 a 5 | — | 4 a 6 | — | — |
| ML42R8FL | — | 1 a 2 | 1 | — | 2 | — | 2 | — | 2 a 4 | — | 3 a 5 | — | — |
| ML42R8FH | — | — | — | 1 | — | 1 | — | 2 a 4 | — | 3 a 4 | — | 3 a 5 | 4 a 5 |
| ML42S1AH | — | — | — | 1 | — | 1 | — | 2 a 4 | — | 3 a 4 | — | 3 a 5 | 4 a 5 |
| ML42S1FH | — | — | — | 1 | — | 1 | — | 2 a 4 | — | 3 a 4 | — | 3 a 5 | 4 a 5 |
| ML49C1FH | — | — | — | 1 | — | 1 | — | 2 a 3 | — | 3 a 4 | — | 3 a 4 | 4 a 5 |
| ML60C2AH | — | — | — | — | — | 1 | — | 2 | — | 2 a 3 | — | 2 a 3 | 3 |
| ML60R9FL | — | 1 | — | — | — | — | 1 | — | 1 a 3 | — | 2 a 3 | — | — |
| ML64R10AH | — | — | — | — | — | — | — | — | — | — | — | — | — |
| ML78C3AH | — | — | — | — | — | 1 | — | 1 a 2 | — | 2 | — | 2 | 2 |

Los valores expresados corresponden a la cantidad de módulos Led que pueden ser manejados por cada driver.
Las especificaciones e informaciones técnicas están sujetas a cambios sin previo aviso.

| DRIVER | OSRAM  | PHILIPS  | | | ELT  | | | | |
|--------------|---|---|---|--|--|---|---|---|---------------|
| | Optotronic Ote 35/220-240/700CS  | Xitanium 36W  | Xitanium 75W  | Xitanium 150W  | 50351412 50351410  | 50355810  | 50701412 50701410  | 50704412 50704410  | |
| MODULO LED | | | | Programable | | | | | |
| | | | | 350mA | 700mA | 350mA 15V-45V | 350mA 35V-85V | 700mA 15V-45V | 700mA 30V-60V |
| ML9R1AL | — | 6 a 10 | 11 a 20 | 14 a 29 | — | 2 a 4 | 5 a 8 | — | — |
| ML12R2AH4500 | 1 | — | — | — | 4 a 7 | — | — | 1 | 2 |
| ML14R3AH4500 | 1 | — | — | — | 3 a 6 | — | — | 1 | 1 a 2 |
| ML15R1AL | — | 4 a 6 | 7 a 12 | 8 a 17 | — | 1 a 2 | 3 a 5 | — | — |
| ML15R4FL | — | 4 a 6 | 7 a 12 | 8 a 17 | — | 1 a 2 | 3 a 5 | — | — |
| ML18R1AL | — | 3 a 5 | 6 a 10 | 7 a 14 | — | 1 a 2 | 3 a 4 | — | — |
| ML18R5FL | — | 3 a 5 | 6 a 10 | 7 a 14 | — | 1 a 2 | 3 a 4 | — | — |
| ML24R5FL | — | 2 a 3 | 4 a 7 | 5 a 10 | — | 1 | 2 a 3 | — | — |
| ML30R6FL | — | 2 a 3 | 4 a 6 | 4 a 8 | — | 1 | 2 | — | — |
| ML33R7FL | — | 2 | 3 a 5 | 4 a 7 | — | 1 | 2 | — | — |
| ML42R8FL | — | 2 | 3 a 4 | 3 a 6 | — | 1 | 1 | — | — |
| ML42R8FH | 2 | — | — | — | 6 a 12 | — | — | 1 a 2 | 2 a 3 |
| ML42S1AH | 2 | — | — | — | 6 a 12 | — | — | 1 a 2 | 2 a 3 |
| ML42S1FH | 2 | — | — | — | 6 a 12 | — | — | 1 a 2 | 2 a 3 |
| ML49C1FH | 2 | — | — | — | 6 a 12 | — | — | 1 a 2 | 2 a 3 |
| ML60C2AH | 1 | — | — | — | 4 a 8 | — | — | 1 | 2 |
| ML60R9FL | — | 1 | 2 a 3 | 2 a 4 | — | — | 1 | — | — |
| ML64R10AH | — | — | — | — | 1 | — | — | — | — |
| ML78C3AH | 1 | — | — | — | 4 a 6 | — | — | 1 | 1 a 2 |

Los valores expresados corresponden a la cantidad de módulos Led que pueden ser manejados por cada driver.
Las especificaciones e informaciones técnicas están sujetas a cambios sin previo aviso.